


LED converter 350 mA, on/off switchable

Article no. 17613020

Light.
For Generations.**Tender**

LED converter 350 mA, on/off switchable. This driver fulfills the requirements for safety lighting systems in accordance with DIN EN 50172 VDE 0108-100:2005-01. This converter is equipped with safety devices which protect it against overvoltage, short-circuit as well as thermal and electric overloads. The input and output terminals are suitable for cables with a cross-section of up to 2.5 mm². Material: Plastic, Degree of protection: according to DIN EN 60529 IP20, Protection class: (EN 61140) II, Current: 350 mA, Voltage: 230V AC 50Hz, Power: 15W, Control: on/off.

| Article data | |
|-------------------|--|
| Article no. | 17613020 |
| GTIN | 4251433918530 |
| Short description | LED converter 350 mA, on/off switchable |
| Material | Plastic |
| Length | 115 mm |
| Width | 34 mm |
| Height | 19 mm |
| Scope of delivery | Plug&Play version with 110 mm P&P output cable |
| Weight | 0.107 kg |

LED converter 350 mA, on/off switchable

Article no. 17613020

Light.
For Generations.

| Operating technology of driver | |
|--------------------------------|----------------------------|
| AC nominal voltage min | 100 V |
| AC nominal voltage max | 240 V |
| Frequenz max. | 50 Hz |
| DC nominal voltage min | 176 V |
| DC nominal voltage max | 280 V |
| Current | 350 mA |
| Protection class | II |
| Degree of protection | IP20 |
| Starting current | 27 A (250 µs) |
| Power min | 1 W |
| Power | 15 W |
| Control | on/off |
| Environment temperature (ta) | 0°C up to 40°C |
| Measure point (tc) | max. +75 °C |
| Version | Plug&Play + connection box |

| Packing data | |
|-------------------------|--|
| Gross weight | 0.164 kg |
| Length of packaging | 100 mm |
| Packaging width | 100 mm |
| Packaging height | 100 mm |
| Disposal at end of life | <p>This product must not be disposed of with household waste. You are obliged, to dispose of such electrical waste separately.</p> <p>By disposing of electrical waste and other old or defective electronics separately, you support recycling or other forms of re-use. In that way you help to take care and to avoid that harmful substances get into the environment.</p> |