
BRUMBERG

LED converter 700mA, Casambi dimmable

Article no. 17772020

Light. For Generations.







Tender

LED converter 700mA, Casambi dimmable. This driver fulfills the requirements for safety lighting systems in accordance with DIN EN 50172 VDE 0108-100:2005-01. This converter is equipped with safety devices which protect it against overvoltage, short-circuit as well as thermal and electric overloads. The input and output terminals are suitable for cables with a cross-section of up to 1.5 mm². Material: Plastic, Degree of protection: according to DIN EN 60529 IP20, Protection class: (EN 61140) II, Current: 700 mA, Voltage: 230V AC 50Hz, Power: 38W, dimmable: Yes, Control: Casambi.

Article data	
Article no.	17772020
GTIN	4251433926733
Short description	LED converter 700mA, Casambi dimmable
Material	Plastic
Length	146 mm
Width	44 mm
Hight	30 mm
Scope of delivery	Plug&Play version with 110 mm P&P output cable
Weight	0.198 kg

All technical data as well as, weight and measurements are based on rated values and had been carefully prepared. We reserve the right to make technical changes which are are important in progressing. Product pictures are examples and can vary from the original. Subject to errors. Date 18.01.2023 Orders are placed under our general terms and conditions under https://www.brumberg.com/en/terms-and-conditions/general-terms-and-conditions-of-sale/

LED converter 700mA, Casambi dimmable

Article no. 17772020

Light. For Generations.

BRUMBERG

Operating technology of driver	
AC nominal voltage min	220 V
AC nominal voltage max	240 V
Frequenz max.	50 Hz
DC nominal voltage min	170 V
DC nominal voltage max	280 V
Current	700 mA
Protection class	
Degree of protection	IP20
Starting current	5A 50µs
Power min	7 W
Power	38 W
Control	Casambi
Enviroment temprature (ta)	-25 °C bis +45 °C
Measure point (tc)	max. +80 °C
Version	Plug&Play + connection box
Power factor	0.95

Packing data	
Gross weight	0.265 kg
Length of packaging	90 mm
Packaging width	55 mm
Packaging hight	109 mm
Disposal at end of life	This product must not be disposed of with household waste. You are obliged, to dispose of such electrical waste separately. By disposing of electrical waste and other old or defective electronics separately, you
	support recycling or other forms of re-use. In that way you help to take care and to avoid that harmful substances get into the environment.